
TRASMETTITORE / RICEVITORE DMX WIRELESS 512 CH

WIRELESS DMX
TRANSCEIVER 512 CH



Reference: ZZENAIR

WIRELESS DMX TRANSCEIVER 512 CH

The ZZENAIR can function as both a wireless DMX transmitter and receiver.

Normally, it operates as a receiver, connecting to the input of fixtures to capture the wireless DMX signal and enable remote connection.

By using the included male-to-male barrel adapter, the ZZENAIR becomes a transmitter. When connected to a lighting console, it transmits the DMX signal to remote fixtures.

It supports 1 DMX universe. If you need to transfer multiple universes, you must install multiple transmitters on different transmission bands.

The device has a total of 7 bands, so it's possible to send 7 DMX universes using 7 transmitters.

Technical specifications:

- Voltage: 5V DC
- Transmission bands: 7
- DMX channels: 512
- Working frequency: 2.4GHz
- Maximum distance in open field: 100m
- Dimensions: 215 x 15mm
- Included: TX / RX conversion barrel adapter; power cable; 220V-5V power supply
- Compatible with: ZZEN126BWP; ZZEN918BWP; ZZEN612BWP; ZZEN912BWP; ZZEN612B; ZZEN615BWP

Want more information about our product?

[Contact us now!](#)