
350W USB/BT/FM PLAYER MIXER AMPLIFIER WITH 6 ZONES

Amp/mixer with integrated media player, bluetooth connectivity, phantom power, FM + DAB radio and remote control included



Reference: ZZONE350PA

Amplifier with BT/USB/FM player

Ampli/mixer with integrated multimedia player, bluetooth connectivity, phantom power supply, FM + DAB radio

Technical specifications

- Power: 350 W
- Speaker outputs: 6 output zones, 100V or 70V & 4 Ohm-8 Ohm-16 Ohm
- Inputs: 4 x Mic, 5 x Line
- Frequency response: 80-16KHz
- Protections: Short circuit, clip, overload, and protection against high temperature
- Power supply: AC230V; 50-60Hz
- Phantom feeding
- Remote control included
- Dimensions: 484x405x88mm
- Weight: 10.9 Kg

Want more information about our amplifier mixer?

[Contact us now!](#)