350W USB/BT/FM PLAYER MIXER AMPLIFIER WITH 6 ZONES



Amp/mixer with integrated media player, bluetooth connectivity, phantom power, FM + DAB radio and remote control included

Reference: ZZONE350PA

Amplifier with BT/USB/FM player

Ampli/mixer with integrated multimedia player, bluetooth connectivity, phantom power supply, FM + DAB radio

Technical specifications

• Power: 350 W

• Speaker outputs: 6 output zones, 100V or 70V & 4 Ohm-8 Ohm-16 Ohm

• Inputs: 4 x Mic, 5 x Line

• Frequency response: 80-16KHz

· Protections: Short circuit, clip, overload, and protection against high temperature

Power supply: 230 V AC, 50-60 Hz or 24 V DC

Phantom feeding

Remote control includedDimensions: 484×405×88mm

• Weight: 10.9 Kg

Want more information about our amplifier mixer?

Contact us now!