

---

# MATRIX MIXER WITH 5 IN AND 3 OUT

MATRIX MIXER WITH 5 IN  
AND 3 OUT

Reference: ZZONE503MX



## MATRIX MIXER WITH 5 IN AND 3 OUT

The new ZZONE amplifier line is designed to meet the needs of careful installers seeking versatility, completeness, and ease of use. The ZZONE503MX model is a mixer designed for 3 independent zones, providing 2 stereo outputs and one mono output. The source signal for each zone can come from 4 inputs, including one with dual front inputs for easy connection of portable devices. Additionally, the 2 microphone inputs offer selectable priority and can be included or excluded from each output zone. This ZZONE503MX mixer provides a complete and versatile solution for managing sound in multi-zone environments.

### Technical Specifications

- System: Amp / Mixer
- S/N depth: >82 dBu
- Cross talk damping: >65 dB
- THD: <0.03%
- Power Consumption: 20 W
- Outputs: Zone 1 - Zone 2 - Zone 3 (mono)
- Inputs: Line-Mic-Aux
- Frequency Response: 20 - 20000 Hz
- Protections: Fuse
- Power Supply: AC supply 115/230V~ 50Hz-60 Hz
- Dimensions: 483 x 44.5 x 191 mm
- Weight: 2.76 Kg

**Want more information about our product?**

[Contact us now!](#)