

---

# 240W ZONE AMPLIFIER WITH USB/BT/FM PLAYER, 4 ZONES

240W ZONE AMPLIFIER WITH  
USB/BT/FM PLAYER FOR 4  
ZONES



Reference: ZZONE4240PA

## 240W Zone amplifier for 4 Zones

4 x 240W Zone amplifier with built-in media player USB + SD card, Bluetooth connectivity, Phantom power, FM + DAB radio.

Integrates 4 amplifiers for 100 V and 8-16  $\Omega$  in a single unit, making it suitable as a 4-zone commercial mixer amplifier.

Input priority levels from high to low: Mute, EMC, Mic1, and remote paging microphone over other inputs. Supports up to 6 remote microphones connected to the amplifier via CAT6 cable.

Supports up to 4 remote control panels connected to the amplifier via CAT6 cable. Remote control and 3-meter cable antenna included.

### Technical Specifications

- Power: 4 x 240 W
- Power consumption: 1150 W
- 3 sources and EMC input matrix distributed across 4 speaker zones
- Speaker outputs: 4 zones, 100V and 8-16 Ohm
- Inputs: 3 x MIC 10mV; Line 150-470mV, 10 K $\Omega$ , unbalanced RCA
- Line output: 0.775 (0 dBV)
- Integrated audio player matrix
- Frequency response: 70-20KHz
- Protections: Short circuit, clip, overload, and high-temperature protection
- Remote control and antenna included
- THD: <0.1%
- Signal-to-noise ratio: >80 dB
- Power supply: 230 V AC, 50-60 Hz
- Phantom power
- Remote control included
- Dimensions (W x H x D): 48 x 9.4 x 40 cm
- Dimensions with antenna (W x H x D): 48 x 9.4 x 44.5 cm
- Weight: 7.4 Kg

**Do you want more information about our product?**

[Contact us now!](#)

---